

Sr. No	Description	QTY	Unit																																				
01	<b>Schedule of Requirement for Supply of Medium Voltage Switchgear Panel (6.6KV, 630A)</b>	01	No																																				
	<table border="1"> <thead> <tr> <th data-bbox="116 204 411 247">Switch Gear</th> <th data-bbox="411 204 1090 247">Basic Technical Data</th> </tr> </thead> <tbody> <tr> <td data-bbox="116 247 411 589">Vacuum Circuit Breaker Draw Out Type</td> <td data-bbox="411 247 1090 589"> <ul style="list-style-type: none"> <li>3 Pole, Rated Current: 630A</li> <li>Rated Voltage: 12KV @50/60HZ</li> <li>Rated short circuit Making current 80KA.</li> <li>Rated Short Circuit Breaking Current: 31.5KA.</li> <li>Rated short circuit Duration 3 Sec.</li> <li>Rated Insulation Level (BIL) 75KV or 95KV</li> <li>Motor Drive: 230VAC.</li> <li>Closing Coil: 230VAC.</li> <li>Shunt Trip Coil: 230VAC.</li> <li>UVT Coil: 230VAC</li> <li>Make: ABB Italy, Schneider France</li> </ul> </td> </tr> <tr> <td data-bbox="116 589 411 640">Bus Bar</td> <td data-bbox="411 589 1090 640"> <ul style="list-style-type: none"> <li>630Amp, 75KV BIL, Copper, Tin Coated, Short Circuit Rating 25KA at @ 1-Sec, Size : 1 x 80 x 10mm</li> </ul> </td> </tr> <tr> <td data-bbox="116 640 411 700">Earthing switch 3 Pole</td> <td data-bbox="411 640 1090 700"> <ul style="list-style-type: none"> <li>Rated Voltage :12KV</li> <li>Rated Short Time Current 25KA @ 1-Sec</li> </ul> </td> </tr> <tr> <td data-bbox="116 700 411 862">Current Transformer 1 Pole, 03 Nos</td> <td data-bbox="411 700 1090 862"> <ul style="list-style-type: none"> <li>Ratio 1200: 600A/1A: 1A. or 5A</li> <li>Protection Core: 15VA.</li> <li>Metering Core: 15VA.</li> <li>BIL: 12KV, 28KV, 75KV.</li> <li>STC 18.4KA@3Sec , Frequency : 50Hz</li> </ul> </td> </tr> <tr> <td data-bbox="116 862 411 922">Feeder Protection Relay</td> <td data-bbox="411 862 1090 922"> <ul style="list-style-type: none"> <li>Multi-Function O/C, G/F, S/C, U/V Protection Relay</li> <li>(Make: GE Multilin , Schneider Micom, ABB)</li> </ul> </td> </tr> <tr> <td data-bbox="116 922 411 956">CT Test Block</td> <td data-bbox="411 922 1090 956"> <ul style="list-style-type: none"> <li>Type: MMLG01, Make: GE or Equivalent</li> </ul> </td> </tr> <tr> <td data-bbox="116 956 411 1041">Energy Analyzer</td> <td data-bbox="411 956 1090 1041"> <ul style="list-style-type: none"> <li>Type: PM 750</li> <li>PT Input: --/220VAC, CT Input: --/1A or 5A</li> <li>Supply : 230VAC, Make: Schneider or Equivalent</li> </ul> </td> </tr> <tr> <td data-bbox="116 1041 411 1169">Voltage Transformer. 1 Pole, 03 Nos</td> <td data-bbox="411 1041 1090 1169"> <ul style="list-style-type: none"> <li>Ratio 6.6KV: v3 / 220V: v3</li> <li>Burdon: 100VA Class 0.5</li> <li>Insulation Level: 12/36/95KV</li> <li>Frequency : 50HZ</li> </ul> </td> </tr> <tr> <td data-bbox="116 1169 411 1221">Ammeter Digital</td> <td data-bbox="411 1169 1090 1221"> <ul style="list-style-type: none"> <li>Measuring input 0...1A.</li> <li>Input frequency 50HZ, Aux supply 230VAC</li> </ul> </td> </tr> <tr> <td data-bbox="116 1221 411 1255">Ammeter Selector Switch</td> <td data-bbox="411 1221 1090 1255"> <ul style="list-style-type: none"> <li>4 Position</li> </ul> </td> </tr> <tr> <td data-bbox="116 1255 411 1289">Indication Lamps</td> <td data-bbox="411 1255 1090 1289"> <ul style="list-style-type: none"> <li>ON, OFF, TRIP, Test Position, 220VAC</li> </ul> </td> </tr> <tr> <td data-bbox="116 1289 411 1323">Push Button</td> <td data-bbox="411 1289 1090 1323"> <ul style="list-style-type: none"> <li>ON, OFF, Lamp Test, Emergency Stop</li> </ul> </td> </tr> <tr> <td data-bbox="116 1323 411 1357">Panel Light</td> <td data-bbox="411 1323 1090 1357"> <ul style="list-style-type: none"> <li>60W, 220VAC, 50Hz</li> </ul> </td> </tr> <tr> <td data-bbox="116 1357 411 1409">Auxiliaries</td> <td data-bbox="411 1357 1090 1409"> <ul style="list-style-type: none"> <li>MCBs, Auxiliary Contacts, Relays, Terminals as per Requirement</li> </ul> </td> </tr> <tr> <td data-bbox="116 1409 411 1528">Panel Type</td> <td data-bbox="411 1409 1090 1528"> <ul style="list-style-type: none"> <li>2.3 mm thick Indoor Type Floor Mounting Free Standing Design with Copper Bus Bar</li> <li>Fully wired complete cubical housing which will be metal clad sheet fabricated totally enclosed</li> </ul> </td> </tr> <tr> <td data-bbox="116 1528 411 1588">Panel Dimensions</td> <td data-bbox="411 1528 1090 1588"> <ul style="list-style-type: none"> <li>H x W x D</li> <li>2200 mm x 690 mm x 1370 mm</li> </ul> </td> </tr> <tr> <td data-bbox="116 1588 411 1673">MV Termination Kit</td> <td data-bbox="411 1588 1090 1673"> <ul style="list-style-type: none"> <li>For MV Power Cable, 300mm, Single Core, 3 Phase Termination at MV Bus Bar and MV Switch gear end.</li> <li>(1x 3 connections at both sides).</li> </ul> </td> </tr> </tbody> </table>	Switch Gear	Basic Technical Data	Vacuum Circuit Breaker Draw Out Type	<ul style="list-style-type: none"> <li>3 Pole, Rated Current: 630A</li> <li>Rated Voltage: 12KV @50/60HZ</li> <li>Rated short circuit Making current 80KA.</li> <li>Rated Short Circuit Breaking Current: 31.5KA.</li> <li>Rated short circuit Duration 3 Sec.</li> <li>Rated Insulation Level (BIL) 75KV or 95KV</li> <li>Motor Drive: 230VAC.</li> <li>Closing Coil: 230VAC.</li> <li>Shunt Trip Coil: 230VAC.</li> <li>UVT Coil: 230VAC</li> <li>Make: ABB Italy, Schneider France</li> </ul>	Bus Bar	<ul style="list-style-type: none"> <li>630Amp, 75KV BIL, Copper, Tin Coated, Short Circuit Rating 25KA at @ 1-Sec, Size : 1 x 80 x 10mm</li> </ul>	Earthing switch 3 Pole	<ul style="list-style-type: none"> <li>Rated Voltage :12KV</li> <li>Rated Short Time Current 25KA @ 1-Sec</li> </ul>	Current Transformer 1 Pole, 03 Nos	<ul style="list-style-type: none"> <li>Ratio 1200: 600A/1A: 1A. or 5A</li> <li>Protection Core: 15VA.</li> <li>Metering Core: 15VA.</li> <li>BIL: 12KV, 28KV, 75KV.</li> <li>STC 18.4KA@3Sec , Frequency : 50Hz</li> </ul>	Feeder Protection Relay	<ul style="list-style-type: none"> <li>Multi-Function O/C, G/F, S/C, U/V Protection Relay</li> <li>(Make: GE Multilin , Schneider Micom, ABB)</li> </ul>	CT Test Block	<ul style="list-style-type: none"> <li>Type: MMLG01, Make: GE or Equivalent</li> </ul>	Energy Analyzer	<ul style="list-style-type: none"> <li>Type: PM 750</li> <li>PT Input: --/220VAC, CT Input: --/1A or 5A</li> <li>Supply : 230VAC, Make: Schneider or Equivalent</li> </ul>	Voltage Transformer. 1 Pole, 03 Nos	<ul style="list-style-type: none"> <li>Ratio 6.6KV: v3 / 220V: v3</li> <li>Burdon: 100VA Class 0.5</li> <li>Insulation Level: 12/36/95KV</li> <li>Frequency : 50HZ</li> </ul>	Ammeter Digital	<ul style="list-style-type: none"> <li>Measuring input 0...1A.</li> <li>Input frequency 50HZ, Aux supply 230VAC</li> </ul>	Ammeter Selector Switch	<ul style="list-style-type: none"> <li>4 Position</li> </ul>	Indication Lamps	<ul style="list-style-type: none"> <li>ON, OFF, TRIP, Test Position, 220VAC</li> </ul>	Push Button	<ul style="list-style-type: none"> <li>ON, OFF, Lamp Test, Emergency Stop</li> </ul>	Panel Light	<ul style="list-style-type: none"> <li>60W, 220VAC, 50Hz</li> </ul>	Auxiliaries	<ul style="list-style-type: none"> <li>MCBs, Auxiliary Contacts, Relays, Terminals as per Requirement</li> </ul>	Panel Type	<ul style="list-style-type: none"> <li>2.3 mm thick Indoor Type Floor Mounting Free Standing Design with Copper Bus Bar</li> <li>Fully wired complete cubical housing which will be metal clad sheet fabricated totally enclosed</li> </ul>	Panel Dimensions	<ul style="list-style-type: none"> <li>H x W x D</li> <li>2200 mm x 690 mm x 1370 mm</li> </ul>	MV Termination Kit	<ul style="list-style-type: none"> <li>For MV Power Cable, 300mm, Single Core, 3 Phase Termination at MV Bus Bar and MV Switch gear end.</li> <li>(1x 3 connections at both sides).</li> </ul>	Fully Wired and Complete in all Respects	
Switch Gear	Basic Technical Data																																						
Vacuum Circuit Breaker Draw Out Type	<ul style="list-style-type: none"> <li>3 Pole, Rated Current: 630A</li> <li>Rated Voltage: 12KV @50/60HZ</li> <li>Rated short circuit Making current 80KA.</li> <li>Rated Short Circuit Breaking Current: 31.5KA.</li> <li>Rated short circuit Duration 3 Sec.</li> <li>Rated Insulation Level (BIL) 75KV or 95KV</li> <li>Motor Drive: 230VAC.</li> <li>Closing Coil: 230VAC.</li> <li>Shunt Trip Coil: 230VAC.</li> <li>UVT Coil: 230VAC</li> <li>Make: ABB Italy, Schneider France</li> </ul>																																						
Bus Bar	<ul style="list-style-type: none"> <li>630Amp, 75KV BIL, Copper, Tin Coated, Short Circuit Rating 25KA at @ 1-Sec, Size : 1 x 80 x 10mm</li> </ul>																																						
Earthing switch 3 Pole	<ul style="list-style-type: none"> <li>Rated Voltage :12KV</li> <li>Rated Short Time Current 25KA @ 1-Sec</li> </ul>																																						
Current Transformer 1 Pole, 03 Nos	<ul style="list-style-type: none"> <li>Ratio 1200: 600A/1A: 1A. or 5A</li> <li>Protection Core: 15VA.</li> <li>Metering Core: 15VA.</li> <li>BIL: 12KV, 28KV, 75KV.</li> <li>STC 18.4KA@3Sec , Frequency : 50Hz</li> </ul>																																						
Feeder Protection Relay	<ul style="list-style-type: none"> <li>Multi-Function O/C, G/F, S/C, U/V Protection Relay</li> <li>(Make: GE Multilin , Schneider Micom, ABB)</li> </ul>																																						
CT Test Block	<ul style="list-style-type: none"> <li>Type: MMLG01, Make: GE or Equivalent</li> </ul>																																						
Energy Analyzer	<ul style="list-style-type: none"> <li>Type: PM 750</li> <li>PT Input: --/220VAC, CT Input: --/1A or 5A</li> <li>Supply : 230VAC, Make: Schneider or Equivalent</li> </ul>																																						
Voltage Transformer. 1 Pole, 03 Nos	<ul style="list-style-type: none"> <li>Ratio 6.6KV: v3 / 220V: v3</li> <li>Burdon: 100VA Class 0.5</li> <li>Insulation Level: 12/36/95KV</li> <li>Frequency : 50HZ</li> </ul>																																						
Ammeter Digital	<ul style="list-style-type: none"> <li>Measuring input 0...1A.</li> <li>Input frequency 50HZ, Aux supply 230VAC</li> </ul>																																						
Ammeter Selector Switch	<ul style="list-style-type: none"> <li>4 Position</li> </ul>																																						
Indication Lamps	<ul style="list-style-type: none"> <li>ON, OFF, TRIP, Test Position, 220VAC</li> </ul>																																						
Push Button	<ul style="list-style-type: none"> <li>ON, OFF, Lamp Test, Emergency Stop</li> </ul>																																						
Panel Light	<ul style="list-style-type: none"> <li>60W, 220VAC, 50Hz</li> </ul>																																						
Auxiliaries	<ul style="list-style-type: none"> <li>MCBs, Auxiliary Contacts, Relays, Terminals as per Requirement</li> </ul>																																						
Panel Type	<ul style="list-style-type: none"> <li>2.3 mm thick Indoor Type Floor Mounting Free Standing Design with Copper Bus Bar</li> <li>Fully wired complete cubical housing which will be metal clad sheet fabricated totally enclosed</li> </ul>																																						
Panel Dimensions	<ul style="list-style-type: none"> <li>H x W x D</li> <li>2200 mm x 690 mm x 1370 mm</li> </ul>																																						
MV Termination Kit	<ul style="list-style-type: none"> <li>For MV Power Cable, 300mm, Single Core, 3 Phase Termination at MV Bus Bar and MV Switch gear end.</li> <li>(1x 3 connections at both sides).</li> </ul>																																						